

Direct Connect Vision Series

Remote Control Operating Instructions



Power On/Off and Changing Modes:

- All features of your new Vision Series will be accessed through the included remote control.
- To turn your light on/off, press the red button on the top left of your remote control as indicated in the image to the right.
- Brightness settings can be selected via the red "-" and "+" buttons on the remote control. Alternatively, there are shortcuts on the remote control for 100%, 80%, 60%, 40%, 20%, and 10% outputs.
- Remote control is powered by a CR2032 battery. Battery life is typically 1 - 2 years. Your Vision Series will not function properly and may not turn on or off when battery needs replacement.

Color Tuning Models ONLY:

- Press the "C/T -" button to shift your light one step warmer in the 7 step range.
- Press the "C/T +" button to shift your light one step cooler in the 7 step range.
- The Neutral button will bring your light to the middle of these 7 steps, approximately 3300K.

Automatic Start Instructions:

- Use the Auto On buttons (ON 3hr / 6hr / 9hr) to set your fixture to turn on for the described duration at the current time each day.
- To disable the Auto On timer, hold the red Off button (O) until the fixture blinks 3x times. This is the ONLY way to disable the Auto On timer. Note that the fixture can be on or off during this process.
- You can, however, program a replacement Auto On timer via the Auto On buttons. This allows you to change both the start time and duration without first disabling the timer. Selecting a new Auto On timer button will overwrite the existing timer.
- You can use the Off timer buttons (OFF 3hr / 6hr / 9hr) independently of the Auto On timer. Should you have an Auto On timer set and select an Off timer option, your fixture will turn off automatically at the described duration of the Off timer selection, though will still turn on the following day at the time previously set via the Auto On timer.
- You can use these Off timer buttons or quick-press the red Off button to modify the time your fixture will turn off without impacting the Auto On timer. You can also use the red On button (|) at any point without impacting the Auto On timer.
- Brightness and color temperature settings are stored on a last used basis. When the fixture turns off, it will turn back on with the same brightness and color temperature settings as previously used.

